

SR5007

7ch Integrated Network Receiver



marantz®



7.2 Channel 4K & 3D Pass Through, Networking Home Theater Receiver with AirPlay

Combining network capability and audiophile sound, the Marantz SR5007 7.2 channel Home Theater Receiver is an ideal media center for any home theater system. With Marantz's classic "star and circle" front display, the receiver offers both style and comprehensive features, including an Ethernet port, six HDMI inputs, and playback of the latest hi-definition audio formats. AirPlay® allows you to stream music wirelessly from your iPhone®, iPod® Touch and iPad® over your home network. Two audio zones and additional support for Bluetooth devices via RX101 make the SR5007 a powerful and versatile solution for all your home theater and music listening needs.

Audio/Video Quality

- Fully discrete power amplifier for all 7 channels (100 W x 7 ch, 8ohm 20Hz-20kHz 0.08%)
- 4K video support (path-through and GUI overlay)
- 3D pass-through technology for enjoying 3D video entertainment with dynamic surround sound
- 1080p/24Hz upscaling via HDMI
- 4K (3840x2160) upscaling via HDMI

Connectivity, Flexibility & Expandability

- Airplay: Stream music from your iPad, iPhone or iPod Touch or from your iTunes music library
- Internet Radio
- Networking Ready: Stream internet radio, Pandora, SIRIUS XM, as well as music and photos over the home network
- Bluetooth wireless connectivity (M-XPort) via optional RX-101 adaptor
- 7.2 Channel Pre-amp outputs allow the connection of external power amplifiers if needed

- Front Panel USB Input Direct digital play for iPod, iPhone and USB drives
- 6 (front:1) /1 HDMI In/Out
 - CEC (Control)
 - ARC (Audio Return Channel)
 - Standby source setting via HDMI control
 - Auto Lip Sync.
 - Deep Color, "x.v.Color"
 - Pass through in standby mode
- Audyssey MultEQ XT setup
- Audyssey Dynamic EQ & Dynamic Volume
- L/R ch. LINE OUT for Zone2
- 2/1 Component In/Out
- 3 (front:1) /1 Composite In/Out
- 2/2 Optical/Coaxial Digital In
- Headphone output
- FM Tuner
- 56 Tuner Presets
- 5 Audio inputs (incl. front input)
- 7.1 ch Input

Ease of Use

- Improved System Setup with menu assist.
- Rich overlay GUI with English, French, or Spanish

- New Simple Remote handset
- Auto Power Off
- Mobile App control with advanced media browsing. (iOS & Android)

Additional Features

- Power amp Assign for 7.1ch (SB ch.), 5.1ch + Front Height, 5.1ch + Bi-Amp, 5.1ch + zone, or 5.1ch + Front B
- 2 source Powered Zone2 capability
- IR Flasher In
- RS232C control (AMX/Crestron command)
- C4 certified (IP/232C)
- Assignable DC trigger (+12V, 150mA x 1)
- Less depth for improving installation
- Firmware Upgradable via Internet

Marantz Audio Advantage

- Pure Direct / Source Direct
- M-DAX (Marantz Dynamic Audio eXpander)
- 192kHz/24-bit Audio DACs
- Transparent binding post speaker terminals

because music matters

Specifications

Audio Section

Power amplifier

Rated output:

Front:

100 W + 100 W (8 ohm, 20 Hz – 20 kHz with 0.08 % T.H.D.)

180 W + 180 W (6 ohm, 1 kHz with 10 % T.H.D.)

Center:

100 W (8 ohm, 20 Hz – 20 kHz with 0.08 % T.H.D.)

180 W (6 ohm, 1 kHz with 10 % T.H.D.)

Surround:

100 W + 100 W (8 ohm, 20 Hz – 20 kHz with 0.08 % T.H.D.)

180 W + 180 W (6 ohm, 1 kHz with 10 % T.H.D.)

Surround back:

100 W + 100 W (8 ohm, 20 Hz – 20 kHz with 0.08 % T.H.D.)

180 W + 180 W (6 ohm, 1 kHz with 10 % T.H.D.)

Analog

Input sensitivity/Input impedance: 200 mV/47 k ohm

Frequency response: 10 Hz – 100 kHz — +1, –3 dB (DIRECT mode)

S/N: 100 dB (IHF-A weighted, DIRECT mode)

Video Section

Standard video connectors

Input/output level and impedance: 1 Vp-p, 75 ohm

Frequency response: 5 Hz – 10 MHz — 0, –3 dB

Color component video connector

Input/output level and impedance:

Y signal — 1 Vp-p, 75 ohm

PB / CB signal — 0.7 Vp-p, 75 ohm

PR / CR signal — 0.7 Vp-p, 75 ohm

Frequency response: 5 Hz – 60 MHz — 0, –3 dB

Tuner Section [FM]

(Note: μV at 75 ohm, 0 dBf = 1×10^{-15} W)

Receiving Range:

FM: 87.5 MHz – 107.9 MHz

Usable Sensitivity: FM: 1.2 μV (12.8 dBf)

S/N: MONO 70 dB (IHF-A weighted, DIRECT mode)

STEREO 67 dB (IHF-A weighted, DIRECT mode)

Total harmonic Distortion (at 1 kHz):

MONO 0.7 % STEREO 1.0 %

General

Power supply: AC 120 V, 60 Hz

Power consumption: 650 W

0.2 W (Standby mode)

0.5 W (CEC standby mode)

2.7 W (network standby mode)

Dimensions (W x H x D):

17 21/64" x 6 11/32" x 13 13/64"

440 x 161 x 335.2 mm

Weight: 22 lbs 4 oz, 10.1 kg

Technology



Front Panel USB Input



Front Panel HDMI Input



Stream music from your iPad®, iPhone® or iPod Touch® or from your iTunes® music library.



New Apps



GUI Overlay with upscaling 4K video



4K video support (Video passthrough, video upscaling)



*Dolby, Pro Logic, and the double-D symbol are registered trademarks of Dolby Laboratories. *DTS, DTS-HD, the Symbol, & DTS or DTS-HD and the Symbol together are registered trademarks of DTS, Inc. © DTS, Inc. All Rights Reserved. *The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries. *Windows Media and the Windows logo are trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries. *Audyssey MultEQ® XT, Audyssey Dynamic EQ® and Audyssey Dynamic Volume® are registered trademarks of Audyssey Laboratories. **Made for iPod, **Made for iPhone, ** and **Made for iPhone, ** mean that an electronic accessory has been designed to connect specifically to iPod, or iPhone, respectively, and has been certified by the developer to meet Apple performance standards. Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards. Please note that the use of this accessory with iPod, or iPhone, may affect wireless performance. *AirPlay, the AirPlay logo, iPad, iPhone, iPod, iPod classic, iPod nano, iPod shuffle and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries. **x.v.Color is a trademark of Sony Corporation. *SIRIUS, XM and all related marks and logos are trademarks of Sirius XM Radio Inc. and its subsidiaries. All rights reserved. Service not available in Alaska and Hawaii.

©2012 Marantz America, LLC.

For purposes of improvement, specifications and design are subject to change without notice. All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, LLC, or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors. Being made by dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

1-855-ONE-MARANTZ

1-855-663-6272

Call for Assistance: 9:00AM to 8:00PM M-F E.S.T.

For frequently asked questions please visit www.marantz.com